

# FS-C FIREscape Addressable Control Panel



The FS-C emergency light control panel features two lines, each line can accommodate 127 exit signs, route lights or I/O units.

The FS-C supplies the operational voltage to the light units during normal conditions, whilst also completing the continuous testing and monitoring of the equipment on the system. All monitored event information is saved in the memory of the control panel, and this can be accessed by a connected FS-KP key pad.

(Shown with FS-KP key pad - Ordered separately)

## Features

- ▼ Complies with BS5266
- ▼ Supports 2 Lighting Lines with 127 Points Per Line
- ▼ Slim Profile - only 100mm Deep
- ▼ Robust Design

| SPECIFICATION                      |                                    |
|------------------------------------|------------------------------------|
| Ordering Code                      | FS-C                               |
| Number of Lights / Signs Supported | 254                                |
| Connection Voltage                 | 35V ac (222 VA)                    |
| Nominal Voltage                    | 12 V dc                            |
| Internal Batteries Capacity        | 7.2 Ah                             |
| I/O Outputs                        | 2 Relay Outputs                    |
| Modem / PC Connection              | RS-232                             |
| User Panel Connection              | RS-485 / 9600 Baud                 |
| Event Memory                       | 500 Events                         |
| Dimensions                         | 295W x 475H x 100D                 |
| Material / Colour                  | Sheet Steel, Powder-Coated / White |
| Weight Including Batteries         | 8KG                                |

**All Correspondence, Registered Office:**

Fire Protection Group (FPG) Ltd, 28 Mill Road Industrial Estate, Linlithgow, West Lothian EH49 7SF  
Tel: 01506 848080 Fax: 01506 847831 Email: sales@fpgltd.co.uk www.fpgltd.co.uk

LINLITHGOW WARRINGTON BELLSHILL LONDON